


## DS-PK1-E-WB Wireless Keypad

The DS-PK1-E-WB series wireless keypad can connect to AX PRO for alarm control and operation. It can also notice alarm by indicator and buzzer.



### Features

- 433 MHz two-way wireless communication
- AES-128 encryption
- Stay/away arming, disarming, alarm clearing for specified area or all areas
- LED indicates the programmed area
- One-Push fire alarm, panic alarm, and medical alarm. Silent/Audible alarm selectable. etc.
- Output control
- Full touch key design with LED backlight
- Fully remote configurable through App
- Multiple enrollment methods and easy installation design
- Easy replaceable battery
- Frequency hopping against jamming for reliable transmission

### Available Models

DS-PK1-E-WB (433MHz)



## Specifications

Model		DS-PK1-E-WB
RF	Frequency	433 MHz
	Modulation	2GFSK
	Distance	900m (open area)
Interface & component	Tamper switch	Supported, front and rear panel tamper-proof
	Power switch	Power on/off
	Buzzer	Supported
	Indicator	4: fault (orange), enrollment/signal (red/green), arm(blue), disarm(green) and alarm (red)
	Backlight	white
	Key	Number key: 0 to 9 Function key: *, #, stay arming, away arming, disarming, and output
Application & protocol	Protocol	Tri-X, two-way communication
Electrical & battery	Power Consumption	Quiescent current: 180 uA Max current: 251mA Voltage: 1.5 VDC
	Battery type	Four AA batteries
	Battery life span	Standby time more than two years
Others	Operation humidity	10% to 90% (No condensing)
	Operation temperature	-10 °C to +55 °C (-4 °F to +122 °F)
	Color	White
	Installation	Screw mounting
	Dimension (W x H x D)	140 (5.50") x 86 (3.38") x 22 (0.87") mm
	Weight	Without batteries: 151 g (5.33 oz), and 23 g (0.81 oz)each battery
Approvals	FCC	Supported
	CE/CB	Supported
	RCM	Supported
	Rohs/Reach/WEEE	Supported

Distributed by

**HIKVISION®****Headquarters**

No.555 Qianmo Road, Binjiang District,  
Hangzhou 310051, China  
T +86-571-8807-5998  
overseasbusiness@hikvision.com

**Hikvision USA**  
T +1-909-895-0400  
sales.usa@hikvision.com

**Hikvision Australia**  
T +61-2-8599-4233  
salesau@hikvision.com

**Hikvision India**  
T +91-22-28469900  
sales@pramahikvision.com

**Hikvision Canada**  
T +1-866-200-6690  
sales.canada@hikvision.com

**Hikvision Thailand**  
T +662-275-9949  
sales.thailand@hikvision.com

**Hikvision Europe**  
T +31-23-5542770  
sales.eu@hikvision.com

**Hikvision Italy**  
T +39-0438-6902  
info.it@hikvision.com

**Hikvision Brazil**  
T +55 11 3318-0050  
Latam.support@hikvision.com

**Hikvision Turkey**  
T +90 (216)521 7070- 7074  
sales.tr@hikvision.com

**Hikvision Malaysia**  
T +601-7652-2413  
sales.my@hikvision.com

**Hikvision UK & Ireland**  
T +01628-902140  
sales.uk@hikvision.com

**Hikvision South Africa**  
Tel: +27 (10) 0351172  
sale.africa@hikvision.com

**Hikvision France**  
T +33(0)1-85-330-450  
info.fr@hikvision.com

**Hikvision Kazakhstan**  
T +7-727-9730667  
nikia.panfilov@hikvision.ru

**Hikvision Vietnam**  
T +84-974270888  
sales.vt@hikvision.com

**Hikvision UAE**  
T +971-4-4432090  
salesme@hikvision.com

**Hikvision Singapore**  
T +65-6684-4718  
sg@hikvision.com

**Hikvision Spain**  
T +34-91-737-16-55  
info.es@hikvision.com

**Hikvision Tashkent**  
T +99-87-1238-9438  
uzb@hikvision.ru

**Hikvision Hong Kong**  
T +852-2151-1761  
info.hk@hikvision.com

**Hikvision Russia**  
T +7-495-669-67-99  
sateru@hikvision.com

**Hikvision Korea**  
T +82-(0)31-731-8817  
sales.korea@hikvision.com

**Hikvision Poland**  
T +48-22-460-01-50  
info.pl@hikvision.com

**Hikvision Indonesia**  
T +62-21-2933759  
Sales.Indonesia@hikvision.com

**Hikvision Colombia**  
sales.colombia@hikvision.com